

The air purifiers

TEKA

Set FilterCase Basic for 2 working places



(Page: 1 for product 97871)

Description

Set FilterCase Basic for 2 working places

This small filter system is suitable for processes that produce very little smoke, like for example repair work at jewelers.


Equipped with 3 filter stages, particles and gasses are separated.

The performance of the system can be adjusted as required with the potentiometer.

Properties

Intake opening (mm):	2 x NW 50
Main filter quantity:	1
Volumetric flow (m ³ /h):	200
max. pressure (Pa):	17,000
Engine power (kW):	0.8
Supply voltage (V):	230
Connection frequency (Hz):	50
Vorfilter:	ISO 16890 ePM20 coarse > 60% (G4)
Filter class:	Fine dust filter with activated carbon filter mat
Sound level (dB(A)):	65
Weight (kg):	17
Width (mm):	280
Depth (mm):	330
Height (mm):	480
Colour:	RAL 9010

Replacement parts



Prefilter for FilterCase Basic, set of 10 pieces

Product No.: 978400011



Main filter 283x206x25mm for FilterCase Basic

Product No.: 978400012



Set carbon brushes for turbine dustoo + FilterCase

Product No.: 9870004